



LIQUID LEAK DETECTION SYSTEMS

FG-BBOX

Digital Black Box

Product Datasheet



- ▶ FG-NET Satellite Device
- ▶ Digital, Fully Addressable
- ▶ Monitoring Up to 3937 ft (1200m) Sense Cables
- ▶ Detection with Location of Faults

Description

The FG-BBOX is a satellite device of the TTK FG-NET Digital Unit. It is monitored by FG-NET via a standard Ethernet network. It expands FG-NET to manage two additional circuits of sense cables with up to 3937 ft (1200 m) of additional sense cables.

The FG-BBOX can be connected with all TTK digital sense cables, for water, acids and oil leak detection.

In the event of a fault on the sense cables connected to the FG-BBOX, the relevant relay contact is activated and the LED on the relevant circuit switched to red.

On the FG-NET unit, the alarm appears on its touchscreen, the responses are identical as a fault on the sense cable physically connected on the FG-NET unit.

Key Advantages

- Scalable System: Up to 25 FG-BBOX units can be added to a single FG-NET system (without exceeding a total number of 500 digital sense cables per FG-NET), ensuring long-term expandability without additional power sources or zoning panels.
- Precise & Simultaneous Leak Detection: Detects and pinpoints multiple leaks at once for water, acids and hydrocarbon leak.
- Reliable & Intelligent Monitoring: Detects cable break faults while maintaining system integrity by continuing to monitor all preceding cables.
- Smart Connectivity & Alerts: Uses TCP/IP (RJ45 Ethernet) for easy integration with BMS via MODBUS/JBUS, and features 4 relay outputs.
- Customizable & Secure: Each sense cable is fully addressable and can be renamed, ensuring clear identification and easy system management.
- Real-Time Indicator Light: The FG-BBOX has no display but features a luminous logo (green or red) for real-time status identification. It can be installed discreetly while all command and control remain centralized on the FG-NET unit.

Technical Data

Compatibility	Digital unit: FG-NET Digital sense cables: FG-EC, FG-AC, FG-OD range Analog sense cables (via FG-DTCS box): FG-ECS, FG-ACS Diversion / Interface boxes: FG-DTC, FG-DTCS, FG-DCTL, FG-DOD
Dimensions & Weight	6.89" W x 8.66" H x 2.17" D (175 mm W x 220 mm H x 55 mm D) 1.76 lbs (0.8 kg)
Sensor Capacity	80 lengths of sense cable (40 x 2 circuits)
Location Accuracy	Water & acids leak detection: +/- 3 ft (1 m) Oil leak detection: section
Operating Languages	NA
Supply Voltage	100-240 VAC, 50/60 Hz
Current	0.13 A (120 V), 0.07 A (230 V)
Power Consumption	15 VA Max
Operating Temperature	5°F to 131°F (-15°C to 55°C)
Case Type	ABS flame retardant UL94V0
Screen Size	No screen
Format	Wall mounted
Ingress Protection	IP40 - Indoor use only
Serial Connection	MODBUS/JBUS RS232 or RS422/485
IT Security	TCP/IP connection (IPv4, IPv6) & Log-In Trap, HTTPS with TLS1.2, RFC 5280: X.509 (PKIC and CRL profile, IEEE 802.1X support, RADIUS or EAP-TLS)
Network	10/100BASE-T; IPv4/IPv6
Numbers of Relays	4 (2 leak + 1 break common fault + 1 power failure relay)
Relay Types	Volt free dry contact (NO, NC, COM)
Power Failure Relay	Activated on loss of supply voltage
Type of Faults Available on the Configurable Relays	Non-configurable
Maximum Relay Switching Voltage	125 VAC and 220 VDC
Maximum Relay Switching Capacity	60 W (30 V x 2A)

Identification Codes

FG-BBOX F	FG-NET's Satellite Device - 2 Circuits Black Box (Wall Mounted) 100-240VAC for TTK Bus 8723
FG-NET F	Digital Touchscreen Leak Detection Panel (Wall Mounted)
FG-NET E	Digital Touchscreen Leak Detection Panel (Rack Mounted)

Certifications



ATEX certified FG-OD range of sense cables and probes can be connected to the FG-BBOX unit.

All the connections in the FG-BBOX must be done with the power supply switched off.
Read carefully the installation procedure for the FG-BBOX unit.

This brochure has been carefully prepared to ensure technical accuracy but is only intended for promotional use. TTK cannot guarantee that the information contained herein contains no errors or omissions, and hence does not accept responsibility related to the use of its equipment. TTK maintain its obligations set forth in the Standard Terms and Conditions of Sale and will not, under any circumstances, assume liability for any incidental damages, indirect or consequential, arising from the sale, resale, use or misuse of this product. The purchaser(s) accept their responsibility as the sole judge(s) of the adaptability of the product for the intended use.
FG-NET, FG-SYS and TOPSurveillance are trademarks of TTK S.A.S. © TTK 2025

■ **TTK USA Inc.** / 100 S. Broad Street, Suite 730 Philadelphia, PA 19110 / Tel. +1 610 304 2270 / www.ttkusa.com / sales@ttkusa.com
■ **TTK Headquarters** / 19, rue du Général Foy / 75008 Paris / France / T : +33.1.56.76.90.10 / F : +33.1.55.90.62.15 / www.ttk.fr / ventes@ttk.fr